

Support Matrix for IBM System Storage DS4200 Express Storage Servers

Supported OS	Supported IBM Servers	Controller Firmware	Multi Path (RDAC)	Host Bus Adapter (HBA)	Interconnect - Fibre Switch	Other
Microsoft Windows 2003 SP1 32 bit (x86) 64 bit (x64) 64 bit (ia64)	xSeries/ System x System x 3950 System x 3850 System x 3800 System x 3755 System x 3650 System x 3550 System x 3500 System x 3400 e326m e326m Dual eServer xSeries *x455 (ia64 only) (2 node support only)	Firmware Version v.06.16.88.00 The above link supports both the firmware and NVSRAM	RDAC Version v.09.01.35.30 *RDAC MPIO Software is included in the Storage Manager Software package.	xSeries/ System x 2GB HBAs Bios 1.47 QLA 2340 QLA 2342 IBM DS4000 FC2-133 IBM FAStT FC-2 IBM DS4000 - Dual Port FC2-133 4GB HBAs Bios 1.12 QLA 2460 QLA 2462 IBM DS4000 PCI-x 4GB HBA drivers scsiport v.9.1.2.11 storport v.9.1.2.17	xSeries/ System x IBM SAN fibre channel switch models: Primary Support 2005-H16 FW: 5.0.1b Secondary Support 2109-F16 FW: 3.1.2a	For additional information on StorPort drivers it is recommended that you search the Microsoft website for the latest StorPort QFE
	BladeCenter LS20-8850 HS20-8843 *HS20-7981-x86 only HS20-8832 HS21-8853 Current code available via IBM Update Express Download the most recent version here. Note: Servers can be used heterogeneously or homogeneously within a 4 node cluster. *All servers support x86 32 bit and x64 64 bit with the exception of the HS20-7981 which supports x86 only and the x455 which supports ia64 only	BladeCenter 2GB HBAs Bios 1.47 IBM HS20 Fibre Channel Expansion Card BladeCenter SFF Fibre Channel Expansion Card 4GB HBAs Bios 1.12 Qlogic 4Gb Standard Fibre Channel Expansion Card Qlogic 4Gb SFF Fibre Channel Expansion Card BladeCenter Drivers scsiport v.9.1.2.11 storport v.9.1.2.16 *Select product above for driver support				