





SHORT SENSITIVITY ADJUSTMENT

This instrument has an internal adjustment for sensitivity of the short test circuit. This control has been set at the factory for a nominal 1 megohm sensitivity. This should be checked occasionally by placing a 1 megohm resistor between pin #3 and pin #8 of socket #8 with the B switch at 6 and the C switch at 3. Should this sensitivity control require re-adjusting, proceed in the following manner:

1. -- Remove panel from case.
2. -- Locate short sensitivity control which is across the short lite socket base.
3. -- Place 1 meg external resistor in test socket as outlined above. Rotate control so that the short lite just comes on, starting from end of control where lite is out.
4. -- Re-assemble tester, be sure to remove 1 meg resistor before testing tubes.

PM-252

NAME _____

ADDRESS _____

CITY & STATE _____ ZIP _____

B & K DIVISION OF DYNASCAN CORP.
1801 W. BELLE PLAINE
CHICAGO, ILL. 60613

CRT

www.everything4lessstore.com

B & K Model 600 Parts and Price List

SCHEMATIC SYMBOL	DESCRIPTION	B & K PART No.	DEALER'S PRICE
------------------	-------------	----------------	----------------

CAPACITORS

C-1	.05 MFD @ 500 V Disc Ceramic Capacitor	CC-A05-500-20	\$.21
C-2	5 MFD @ 250 V Pigtail Electrolytic Capacitor	CL-5-250	.72
C-3	250 MFD @ 6 V Pigtail Electrolytic Capacitor	CL-250-6	.84
C-4	.01 MFD @ 500 V Disc Ceramic Capacitor	CC-A01-500-20	.09

RESISTORS — CONTROLS

R-3	100K Ohm ¼ Watt Control, "Gas Sensitivity Adjust"	P-62	.57
R-6	1 Megohm Control (Short Adjust)	P-44	.42
R-7	1K Ohm—3 Watt 10% Glass Resistor	RG-103-3-10	.18
R-9	1K Ohm—4 Watt Wire Wound Pot. (Special Taper) "A" Control	P-22	2.16

SWITCHES

SW-1	Heater Switch	S-7	.99
SW-2	"C" Selector	S-53	1.38
SW-3	"B" Selector	S-55	2.31
SW-4	"Quality" Push Button Switch	S-38	1.62
SW-5	"Grid Emission" Push Button Switch	S-60	1.44
T-1	Transformer, Power	TP-17	5.43
M-1	Meter	ME-11	12.15
V-1	6BN8 Tube	V-6BN8	1.51

MISCELLANEOUS PARTS

Plate-Grid Cap Assembly	ASM-45	.63
Test Sockets No. 1, No. 6 (7 Pin Min.)	G-7PF	.12
Test Socket No. 7 (Noval)	G-9PF	.15
Test Sockets No. 3, No. 8 (Octal)	G-8PF	.12
Test Socket No. 4 (Loctal)	G-8L	.18
Test Socket No. 5 (Nuvistor)	G-12	.21
Test Socket No. 2 (10 Pin)	G-10	.75
Test Socket No. 9 (12 Pin)	G-34	.75
Novar Test Socket	G-35	.15
7 Pin—Pin Straightener	H-259	.09
9 Pin—Pin Straightener	H-260	.09
Line Cord Strain Relief	H-195	.06
Bar Knob	K-21	.15
Carrying Case	LG-7	7.20
"Shorts" Lamp (NE-51)	PL-1	.45
"Shorts" Lamp Socket	LS-1	.33
"Shorts" Lamp Clear Plastic Cap	LS-1-C	.15
Carton & Fillers	PKG-70	.57
6-foot Black Line Cord	W-14	.30

(Prices subject to change without notice.)

Note: Standard value resistors are not listed.
Values may be obtained from schematic diagram.

Minimum charge \$1.00 per invoice. Orders will be shipped C.O.D. unless previous open account arrangements have been made or remittance accompanies order. Advance remittance must cover postage or express charges.

